



Ear-Worn Microphone for use with RF-TX1

RF-TX1-EM

This ear-worn microphone is compatible with the Portable Radio Frequency Transmitter [RF-TX1-865/915]. It comes with a 1.2m cable and mini-XLR connector. Enables handsfree communication with clear sound using a high quality Condenser microphone capsule.

Physical Data

Dimensions	Height - 60mm (2.3") Width - 32mm (1.25") Depth - 160mm (6.2") Lead Length - 1.2m (47.2")
Weight	10.5g (0.02lbs)
Finish	Beige

Technical Data

Connector	Mini-XLR
Power Supply	1 ~ 10V / DC phantom voltage
Transducer Type	Condenser capsule
Polar Pattern	Unidirectional
Sensitivity	-47 ± 3 dB @f = 1 kHz, S.P.L = 1Pa, 0 dB=1V / 1pa -67 ± 3 (0dB = 1 V/microbar)
Frequency Response	70 - 16kHz

Applications

Ideal for tour guidance or private group interactions:

- Museums
- Historical Sites
- Exhibitions/Events/Conferences
- Outdoor Tours



Talk to us now:
+44 (0) 1732 223900 (UK & ROW)
+1 616 392 3400 (US & Canada)
www.contacta.co.uk