



Lapel Microphone for use with RF-TX1

RF-TX1-LM

This lapel microphone is compatible with the Portable Radio Frequency Transmitter [RF-TX1-865/915]. It includes a tie clip and 1m cable with a mini-XLR connector. It enables handsfree communication with clear sound using a high quality Condenser microphone capsule.

Physical Data

Dimensions	<p>Mic: Height – 11.4mm (0.44") Width – 11.4mm (0.44") Depth – 24.7mm (0.97") without clip</p> <p>Clip: Height - 6.5mm (0.25") Width - 44.2mm (1.74") [40.5mm (1.59") without clip]</p> <p>Lead Length - 1000mm (39.3")</p>
Weight	24g (0.05lbs) with clip
Finish	Black

Technical Data

Connector	Mini-XLR
Power Supply	1 ~ 5V / DC phantom voltage
Transducer Type	Condenser capsule
Polar Pattern	Unidirectional
Sensitivity	-50 ± 3 dB @f =1 kHz, S.P.L=1 Pa, 0 dB=1V / Pa
Frequency Response	180 Hz - 17kHz

Applications

Ideal for tour guidance or private group interactions:

- Museums
- Historical Sites
- Exhibitions/Events/Conferences
- Outdoor Tours